

DC - DC CONVERTER 120W







All dimensions in mm

•	DC Inp

FEATURES

- DC Input Built In Transient protector & EMI filter
- Protection against short circuit, overload & overvoltage Low ripple & noise

- Power OK indication, terminations, output set control & rating details on front
- 100% full load burn in tested Low cost
- High reliability

	Cooling by free air convection Compact		
ISOLATION	Input – Output : 1.5KVAC, 1 minute Input – Earth : 1.5 KVAC, 1 minute Output – Earth : 0.5KVAC, 1 minute		
EFFICIENCY	70 ~ 75%		
O/P VOLTAGE ADJUSTMENT	+/- 10% of nominal output voltage		
OVERLOAD PROTECTION	105% ~ 130% of rated load		
LINE & LOAD REGULATION	Better than 0.5%		
OPERATING AMBIENT	0 ~ 50°C, 95% RH		
STORAGE AMBIENT	-20°C to 85°C		
SAFETY STANDARD	Design refers to EN60950-1		
EMC STANDARD	Design refers to EN55022, EN55024		
TERMINATIONS	Screw type, for 2.5mm sq. wire		
MOUNTING	35 mm DIN rail		
WEIGHT	530 grams		

ORDERING INFORMATION		NOMINAL INPUT: 24VDC	ОИТРИТ		OVERVOLTAGE PROTECTION
	INPUT RANGE	18 to 36VDC			
	I/P CURRENT (max)	6.0A @24VDC			
	ORDER CODE	G34-120-24	24V: 4.0A	< 240mV	< 30V

Note:

- All parameters measured at nominal input, rated load and 25°C of ambient temperature unless otherwise specified.
 Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 100uf parallel capacitor.
 The power supply is intended to be install as a component inside the enclosure of final equipment. The final equipment must be re-confirmed that it still meets the EMC directives.

 4. These units are designed for mounting on horizontal DIN rail. Ensure clearance of minimum 35mm from adjacent components for proper ventilation.

Rev. 1

Unit No:G-5/6, B Wing, Plot K-3, Udyog Bhavan No:2, Anand Nagar MIDC, Ambernath(E) 421506, MH, India. Boardlines: +91-251-2620417, 2620427 Cell: +91-9820362980 Email: shavison@shavison.com www.shavison.com